

Alarm and control unit FS1A8P



Alarm and control unit FS1

Product features

- Alarm and control unit for max. 7 digital inputs (e.g. contact pressure gauge or pressure switch), 8 analogue inputs (e.g. pressure transmitters or weighing scales) and one additional input for an external emergency shut off
- The unit may be configured for 1 individually programmable pneumatic valve
- Touchscreen operation: all operation from ergonomically positioned Human Machine Interface
- Industrial PLC controls all inputs and outputs as well as analogue signal processing
- Monitoring and display of the gas content by pressure or weight
- Relay output for the valve status
- Communication options: Ethernet and Modbus RTU
- Solenoid valves / relay can be manually operated
- Daylight visible LED indicators
- Acoustic signals can be silenced
- Digital inputs to be configured for NO or NC contacts
- All parameters and signal configurations can be programmed with the touch panel at the front of the unit
- Plastic housing IP 65 for wall mounting
- Emergency shut off
- Password protection for 2 superior levels of access
- Multiple Language Support: German / English
- According to Low Voltage Directive 2006/95/EG

Technical data

Housing

Protection class:	IP65
Dimensions:	300 x 320 x 200 mm

Compatible Inputs

- mechanical switches
- electr. switch PNP/NPN (DC only)
- analogue sensors (4-20 mA)

Relay outputs

max. switch-able voltage:	30 V DC
max. switch-able load:	8 A

Pneumatic output

Actuator pressure:	max. 7 bar
Actuator connector:	for hose Ø 4mm

Power supply voltage:	110-230 V AC / 50-60 Hz
max. current:	1,5 A

Communication parameters RS-232

Baud rate:	19200
Polarity:	1 Stopbit 8O

Applications in explosive environment

The control unit FS1 must be mounted *outside of explosive environment*. Inductive sensors, which are installed inside hazardous areas, have to be activated by an ATEX-approved switch amplifier. This amplifier also has to be mounted *outside of explosive environment*. The output contact of the switch amplifier can easily be connected to the control unit.